

## 12core MT Ferrule ~Single Mode Low Loss~

### ◆◆◆ Feature ◆◆◆

- Low loss performance
- Japan made



12 core MT ferrule designed and manufactured with low loss performance for high demand network. Mating test results with major MT ferrule manufacturers are also good. We have the product line in Japan.

### ◆◆◆ Specification ◆◆◆

(Unit: mm)

| Type              | Eccentricity | Guide Hole Pitch | Guide Hole Diameter | Fiber Hole Diameter | Insertion Loss* |
|-------------------|--------------|------------------|---------------------|---------------------|-----------------|
| MT-12 SM Low Loss | < 0.0007     | 4.598~4.602      | 0.6990~0.6996       | 0.1252~0.1258       | max ≤0.35dB     |
| MT-12 SM Standard | < 0.0014     | 4.598~4.602      | 0.6990~0.7000       | 0.1253~0.1265       | max ≤0.70dB     |

\*Insertion Loss = Connector loss + Fiber loss

For more information, please contact our sales team : [info@setodenshi.com](mailto:info@setodenshi.com)



**SETO ELECTRONICS CORPORATION**  
 2-31, Kohan-cho, Seto, Aichi, Japan  
 email: [info@setodenshi.com](mailto:info@setodenshi.com)  
<http://www.setodenshi.com/>

**【Oversea Network】**  
 Hongkong /Danang (Vietnam)  
 /Shenzhen /Wuhan/Xiangyang (China)